



1) 1st pos.



### Basic features

### Additional features

Safety switch positions acc. to  
DIN EN 30204-1/VDE 0113 may  
only be used with rigid plunger!

Mechanical Cam Switches  
**BNP 23-02-D12-61-A-01**  
Order Code: BNP000J

**BALLUFF**

Approval/Conformity	CE WEEE
Use with series	BNS 823-...-61-..
Version	Safety

**Material**

---

Plunger material	1. Switch position: Stainless steel (1.4034)
Surface protection	Anodized

**Mechanical data**

---

Dimension	26 × 35 mm
Number of switching positions	2x Chisel
Plunger spacing 1st switch pos. (M)	12 mm
Plunger style	1-2nd switch position: Chisel
Rail material	Aluminum
Switch positions	1. Switch position: Safety 2. Switch position: Standard

**Range/Distance**

---

Switch position spacing	12 mm
-------------------------	-------